

UPS600-2

600W Portable Power Station

Datasheet



Dimension: 258mm*212 mm*249mm

Weight: 6kg

Materials: PC (Top and Bottom) + ABS (Middle Frame)

Specifications

Item	Rating	Remark
Battery		
Category	Li-ion 21700 Battery	
Rated Capacity(mAh)	576Wh	3C Discharge
Nominal Voltage(V)	3.6V	
Cut Down Voltage	3.0V	
Maximum Charge Voltage	4.2V±0.05V	
Charging Method	CC/CV	Charge with constant current 0.2C to 4.2V, then charge with constant voltage 4.2V till charge current is less than 0.01C
Initial Internal Resistance	≤25mΩ	
Cell Dimension(mm)	180*115*75mm	Battery Pack Size
Weight	3.1kg	Battery Pack Weight
Operating Temp for Charging(°C)	0°C~45°C	
Operating Temp for Discharging(°C)	-10°C~45°C	
Storage Temp(°C)	-20°C~55°C	Less than 1 month
	-20°C~45°C	Less than 3 months
	-20°C~25°C	Less than 1 year
Cycle Life	≥1000 Times	Charging: 0.2C Constant Current and constant voltage charged to 4.2V, current less than or equal to 0.02C will be cut off. Discharging: 0.2C discharge to 3.0V will be cut-off. When the discharge capacity drops to 80% of the standard capacity, the test is stopped.

Performance

Charging Method	CV/DC	Mode of Input Voltage
USB1/USB2(Output)	5V=3A;9V=2A;12V=1.5A	QC18W
USB-C Port(Output)	5V=2.4A;9V=3A;12V=2.25A	PD27W
USB-C Port(Output/Input)	5V=2.4A;9V=3A;12V=3A;15V=3A;20V=5A	PD100W
DC1/DC2/DC3/Car Charger(Output)	12V~13V=8~10A	
AC Port(Output)	110V~220V/50Hz~60Hz	600W
DC(Input)	5~24.5V=2~5A	

Portable Power Station

Quiescent Current(uA)	≤400uA	Standby Current less than 400uA
Input Protection Voltage	25V	
Over Discharging Protection Voltage(V)	2.7±0.25V 12V	When the voltage is below 3.0V, the output voltage is disconnected by the system.
Over Current Protection current(A)	50~60A	When the output current is too large, the output voltage will be disconnected.
Short Circuit Protection	Support short circuit to automatically recover	When the positive and negative terminals of the output short-circuit, the output voltage will be disconnected by the system.

Other Features

Output Waveform	Pure Sine Wave	
Total Output Power(W)	600W(1200W at peak)	
Output Ripple Voltage(mV)	≤500mV	
Charging Time(h)	5.5h~7h	Theoretical Charge Time
Solar Panel Power	18V/40W/60W/80W/100W	Affected by sunlight intensity
LED Power	11W	
Battery Maintenance	Charge Every 3 Months	
Working Life	1000 times	Capacity ≥80%
Highest Temperature Inside		When the output is full, the output is turned off at over temperature.
Highest Temperature Outside Surface		When the output is full, the output is turned off at over temperature.
Start When Pressing the Button		Start when pressing the button or inserting.
Power OFF		If the load cannot be detected within 30 seconds after starting the output, it will be automatically Closed. Low power, short circuit, overload, overheating will shut down the output.
Minimum Output Current(min)	60±20mA	Minimum output current without load.
	30S	After button be pressed.
Delay Time to Power Off	35S	If there was a load lower than 50mA and keeps for about 40 seconds, output will be closed then device will sleep at once.

LED Display

Display After Press the Button or Insert Loading		LCD Display Screen to indicate the current discharging details.
		There are tolerance for remaining capacity estimate.
Display When Charging		LCD Display Screen to indicate the current charging details.
		There are tolerance for remaining capacity estimate.

Version: V1.1, updated 2022.11.16.

The information in this document is subject to change without notice.

Every effort has been made in the preparation of this document to ensure accuracy of the contents, but all statements, information, and recommendations in this document do not constitute a warranty of any kind, express or implied.